# **OT-01**

Optical infrared detector for triggering data acquisition in Doppler radar systems

### **General Description**

The Infinition Inc. optical detector can be used to detect the flash of projectiles exiting the muzzle, ignition of rocket motors, squibs, explosions, etc.

- Based on large silicon detector (100mm² detection surface);
- 75mm plano-convex lens used to focus the light on the detector;
- High gain FET amplifier using a photoconductive (biased) circuit configuration for fast rise time (fast detection) and high sensitivity;
- No sensitivity adjustment required. The light detector is AC coupled to the amplifier;
- Analog differential signal output for higher immunity against environmental electrical noise;
- Mounting on standard photo tripod using 1/4-20 mounting screw.
- Very rugged construction made of aluminum.



#### **Specifications**

| Lens Diameter              | 75 mm  |
|----------------------------|--|
| Lens Focal Distance        | 75 mm  |
| Field of View              | 7.6 degree                                   |
| Detector Spectral Response | 600 – 1050 nm                                |
| Detector Area              | 100 mm2                                      |
| Output Signal (nominal)    | +/-2 Volts differential, 50 Ohm              |
| Rise-time                  | < 5 µsec<br>(200kHz frequency response min.) |
| Power Supply               | 12 Volt, 12 mA                               |
| Weight                     | 3.6kg  |

# **AT-01**

Acoustic transducer for triggering data acquisition in Doppler radar systems

#### **General Description**

The Infinition Inc. acoustic transducer has been designed to detect very strong soundwaves generated by various gun firings.

- Includes a piezoelectric pick-up and a built-in amplifier to provide operation over long ranges;
- Power and signal share the same cable, allowing a simple coaxial cable to be used;
- No sensitivity adjustment required;
- Analog differential signal output for higher immunity against environmental electrical noise;
- Mounting on standard photo tripod using ½-20 mounting screw.
- Heavily rugged construction allows the transducer to be placed extremely closed to the muzzle;



### **Specifications**

| Output Signal | +/-3 Volts    |  |
|---------------|---------------|--|
| Power Supply  | 12 Volt, 2 mA |  |
| Weight        | 1.0kg         |  |



sales@infinition.com

www.infinition.com